



Блок производства AV, который позволяет легко создавать AV в ситуациях, когда имеется ограниченное количество доступных операторов, например, университетские спортивные состязания, прямые трансляции и видеопроизводство на конференциях.

AV-HLC100 - Центр потокового вещания

Сочетая функции коммутатора 1ME, контроллера PTZ-камеры и аудиомикшера в одном устройстве, AV-HLC100 позволяет одному человеку управлять всем, от съемки с PTZ-камеры до потоковой передачи.

Key Features

Коммутатор 1ME, контроллер PTZ-камеры и аудиомикшер позволяют одному человеку управлять всем, от съемки PTZ-камерой до потоковой передачи.

Поддержка выходного формата включает 1080/59,94р и 50р; также доступна функция перекрестного преобразования (между 1.080 и 720)

Создавайте собственный великолепный мультимедийный контент для прямых трансляций и потокового видео.

Поддерживаемый сетевой протокол: NDI™ и RTMP (прямая передача на службы потокового вещания, такие как YouTube Live)

3D-джойстик с панорамированием, наклоном и масштабированием позволяет управлять одной рукой



AV-HLC100 - Центр потокового вещания

<https://eu.connect.panasonic.com/global/ru/products/broadcast-proav/av-hlc100-centr-potokovogo-veschaniya>

Power Supply	DC 19 V (AC adaptor provided)
Power Consumption	110 W
Ambient Operating Temperature	0 °C to 40 °C (32°F to 104°F)
Humidity	20 % to 80 % (no condensation)
Mass	Approx. 6.05 kg (13.34 lbs)
Dimensions (W x H x D)	427 mm x 93 mm x 278 mm (16.8 inches x 3.67 inches x 10.96 inches) (excluding protrusions)
Number of ME	1ME
Number of switcher channel	10 <ul style="list-style-type: none"> • 8 External (selected from among 3G-SDI x 4, 3G-SDI x 3 + HDMI x 1, NDI sources x 8) • 2 Internal (CLIP x 1, STILL x 1)
Number of Keyer	2 Keyer (PinP / Title)
System Video Format	1080/59.94p*1 *2, 1080/59.94i, 1080/29.97PsF, 1080/23.98p, 1080/50p*1 *2, 1080/50i, 1080/25PsF 720/59.94p, 720/50p, 720/29.97p, 720/25p
Video Input	SDI x 4 or SDI x 3 + HDMI x 1*1 *3
Network Input Sources	8 <ul style="list-style-type: none"> • NDI input from Panasonic PTZ Camera that supports NDI HX and NDI compatible equipment • IP input from Skype TX compatible PC
Audio Input	15 <ul style="list-style-type: none"> • 4-channel SDI/HDMI embedded audio x 4 • 4-channel NDI embedded audio x 8 • 6.35 mm balanced line x 2 • 3.5 mm diameter, stereo mini jack x 1
Video Output	4 <ul style="list-style-type: none"> • BNC x 1 3G-SDI (PGM)*1 • BNC x 1 3G-SDI (selectable from PGM / PVW / AUX)*1 • HDMI x 1 or Display Port (for GUI)*4 x 1 • Network output x 1
Network Video Output	1 selectable from MIX (PGM or PVW) / AUX <ul style="list-style-type: none"> • NDI output • RTMP format streaming output*5
Audio Output	6 <ul style="list-style-type: none"> • SDI embedded audio x 2 • 6.35 mm balanced line x 2 • 3.5 mm diameter, stereo mini jack x 1 • NDI embedded audio x 1
Effects and Transitions	Wipe / Mix / Cut <ul style="list-style-type: none"> • Background Video • PinP • Title
Audio Mixing	<ul style="list-style-type: none"> • 4 ch. Master (Program) mix • 12 x faders: 1 for each of 8 external audio inputs, plus 1 x internal Clips player and 1 x Skype TX Talkback input; plus 1 x Master output and 1 x Headphones • Plus 1 x separate audio fader for video Streaming output • Seven-band equalizer and stereo compressor / limiter per input and output, with per-input audio delay control
Video Clip Memory	DDR x 1 ch*6
Still Store Memory	DDR x 1 ch*6

Title Buffer	1 Title Buffer (displays 1 of 8 Buffer presets)
Reference Input	Internal only
PTZ Camera Control (Via IP)	<p>Number of connected cameras: Up to 8 cameras</p> <p>Pan / Tilt / ZOOM / FOCUS control: 3 axis joystick (ZOOM / FOCUS is switched by pressing the upper button)</p> <p>ZOOM control: Independent rocker switch</p> <p>IRIS control: independent IRIS knob, pressed AUTO / manual switching</p> <p>FOCUS control: Independent FOCUS knob, pressed AUTO / manual switching</p> <p>Preset control: store / recall, up to 100 positions</p> <p>OSD menu control: OSD button*7</p> <p>White balance control: GUI screen Camera menu or OSD screen (Auto / PST A / PST B / Execute)*7</p> <p>CAM / BAR selection: GUI screen Camera menu or OSD screen*7</p>
Tally Output	DB-15 Tally port
Network Connector	RJ-45 x 2 1000BASE-T / 100BASE-TX / 10BASE-TX
USB Host I/F	USB3.0 x 4
Accessory	AC adaptor, Power cable, keyboard, mouse
Note	<p>*1: 3G-SDI corresponds to Level-A only.</p> <p>*2: The 1080/59.94p and 1080/50p formats are not supported for HDMI input.</p> <p>*3: You cannot use the SDI input 1 and the HDMI connector at the same time.</p> <p>*4: HDMI and Display port can not be used simultaneously.</p> <p>*5: Only available when plug-in provided by NewTek is installed.</p> <p>*6: See "Supported Formats" on page 6 for details.</p> <p>*7: OSD function is available for Panasonic PTZ camera of SDI and HDMI output. It is not available for those of NDI HX output.</p>