



## Camera control panel

# AW-RP120

Highly Functional Remote Controller with joystick and possibility to store settings onto SD card.

### Key Features

Smooth Pan/Tilt Control with joystick

Preset / Tracing memory functions

Color image adjustment function

Flexible System Design by using IP connection and control

IP connection allows a large-scale, flexible, and simple system configuration for controlling up to 100 remote cameras and the simultaneous use of multiple controllers



## AW-RP120

<https://eu.connect.panasonic.com/ch/en/products/broadcast-proav/aw-rp120>

<b>Power Supply</b>	DC 12 V
<b>Accessories</b>	This unit does not include a power supply. Requires AW-PS551P.
<b>Power Consumption</b>	8 W
<b>Weight</b>	Approx. 3.1 kg (Approx. 6.9 lb)
<b>Dimensions (W x H x D)</b>	Approx. 342 mm x 77 mm x 265 mm (Approx. 13-1/2 inches x 3-1/16 inches x 10-7/16 inches) excluding protrusions (Approx. 13-15/32 inches x 3-1/32 inches x 10-7/16 inches) [excluding protrusions]
<b>Connectors</b>	DC 12 V IN (XLR 4-pin)  LAN (RJ-45) 10BASE-T/100BASE-TX, to control remote cameras SERIAL (RJ-45) RS-422, to control remote cameras × 5 TALLY/GPI (D-sub 25-pin) REMOTE (D-sub 9-pin) RS-232C, for external control